

4WINTEGRFITED

	EMERGENCY LED DRIVER				
and i	Input unto	100-240Vac Input voltage 200-240Vac 50/60Hz 100-277Vac	Output power: 22W 3W 4W	Ta:50C Output	
	Black L CE	Input current: 100mA max.	Output voltage: 10-60Vdc	LED, Purple	12100
9412 1091	RoHS	Input power: 4W max.	Charging time:≥ 24 Hours	LED Blue DRIVER + Brown	Annanatii
	Green PG	Emergency time: 11H 1.5H 2H	Charging current:≤ 300mA	DRIVER - Blue	E.
		Output current: 30mA 50mA 60mA]70mA □90mA]80mA ■100mA □		
- Marine					
				- /	
	-				

ELB-0460-FM is a CEC-Compliant, UL-Listed and approved for field installation emergency lighting system for fixtures with **Isolated** drivers. For use with LED modules driven by a constant current source. With the battery, driver, and charger all integrated in a mini housing, it is a perfect choice for installation inside small light fixtures up to 40W.


Applications:

- Flush-Mount ceiling lights
- Cloud ceiling fixtures
- Wraparound lights
- Outdoor wall packs with small housing



Case- 5.5"x1.37"x0.86"(mounting center-5.1")





ELB-0460-FM

Input Voltage	120~277V AC, 50-60Hz		
Input Current	100mA Max.		
Input Power	5W Max.		
Output Voltage	10-60V DC		
Output Current	30-100mA		
Output Power	4W Max.		
Emergency Duration	90 Minutes		
Battery	Li-ion (Lithium-ion), 3.7V / 2500mAh		
Charging Time	≥ 24Hrs.		
Operating Temperature	32°F ~ 104°F		
Test Switch	Test Switch w/ Integrated Indicator Light		
Weight	0.35 lbs.		

